# MGate EIP3170/EIP3270 Series

## 1 and 2-port EtherNet/IP-to-DF1 gateways



#### **Features and Benefits**

- PCCC objects for Rockwell Automation networks supported
- · Use ProCOM to implement control via COM port mapping
- 8 simultaneous EtherNet/IP client/server pairs with up to 16 queued requests
- Serial redirector keeps the original serial master and slave connection while connecting devices to the Ethernet
- · EtherNet/IP and DF1 traffic monitor for easy troubleshooting
- Redundant dual DC power inputs
- · Built-in Ethernet cascading for easy wiring
- -40 to 75°C wide operating temperature models available

#### Certifications



## Introduction

MGate<sup>™</sup> EIP3000 gateways provide Ethernet/IP-to-DF1 protocol conversion for users who need to connect Allen Bradley PLCs to an EtherNet/IP network. With a number of innovative functions, the MGate<sup>™</sup> Series overcomes the difficulties of connecting between legacy serial devices and SCADA software. Both 1 and 2-port gateways are available for use with different-sized control networks.

#### Protocol Conversion between DF1 and EtherNet/IP

By supporting PCCC objects on CIP, the MGate<sup>™</sup> EIP3000 can communicate seamlessly with SCADA software such as RSLinx. For users who develop control software based on EtherNet/IP, the MGate EIP3000 offers the standard interface for connection.

#### **Support for Multiple EtherNet/IP Connections**

MGate<sup>™</sup> EIP3000 gateways support up to 16 EtherNet/IP clients and servers simultaneously. Each client can send up to 16 requests at a time, and the multiple connection capability can help establish redundancy for more complex control systems.

#### Windows Utility for Easy Configuration and Traffic Monitoring

Moxa provides a user-friendly Windows utility with multi-language support. The utility supports a traffic monitoring function for EtherNet/IP and DF1 protocols, and not only logs events initiated by the gateway, but also records all commands and responses that pass through the gateway. The utility helps users determine the root cause of failures and performance bottlenecks.

.000 IP 192.14 .025 GW Seria .045 GW Seria	5 Direction 68.32.43>GW 9 Port 1> 9 Port 1<	Type Command Command ACX		OF OF	07 40 00 A7 36 AA 01 0F 00 40 66 A3 FF 40 04 10 02 00 00 0F 00 40 66 A3 FF 40 04 FF 4E 04		
.025 GW Seria .045 GW Seria	I Part 1> I Part 1<	Command					
.045 GW Seria	Port 1 <						
				-		OF1 Transmission symbol	
	Part 1 <	Reply		10	10 02 00 08 47 00 40 66 00 00 00 00 69 00 00		
	Part 1->	ACK				OF1 Transmission symbol	
				10	07 4D 00 47 36 44 01 47 00 43 66 03 00 00 00		
		Connard		05	07 40 00 47 36 64 01 05 00 41 66 03		
	Doug 1 and	Command		05	10 02 03 00 06 00 41 66 03 10 03 85 12		
		ACX.				OF1 Transmission symbol	
	Doub 1 Kin	Dumby		44	10 12 00 05 96 00 41 66 00 FF 36 42 56 35 25 3		
	Doug Lock	ACK	-			CF1 Transmission symbol	
				44	07 40 00 57 36 45 01 46 00 41 46 00 FF 34 40	Ct 1 Indianaster syneet	
.280 JP 192.16	68.32.43 WW	Command		05	07 40 00 A7 36 6A 01 0F 00 47 66 43 FF 40 04		
	d there have been been been been been been been be	Connard		05	10 12 03 00 0F 00 42 66 43 FF 40 04 FF 4F 04		
						Pdit Texperitories conched	
				-	10 10 00 00 00 00 00 00 00 00 00 00 00 0	of a management symposi	
						PET Transmission cumbel	
				46	02 40 00 47 36 45 01 45 00 47 66 00 00 00 00	or i mananisation sympton	
				~	10 12 00 10 00 10 10 00 10 00 01 14	PET Transmission cumbel	
				46	10 12 00 10 46 10 42 46 00 55 34 45 00 35 35 3	of I mananaport sympos	
				**		PET Temperaturing cumbel	
				46	02 40 00 57 36 65 01 46 00 42 66 00 FE 34 48	or I mananananananan	
				· ·	to the option of the map with the of the	DE1 Transmission combol	
				45	10 02 00 02 45 00 44 66 00 00 00 00 42 00 00	and a management of Symposi	
					10 CL 00 CO 4 CO 11 CO 00 00 00 00 A2 CD 00	OEI Transmission combol	
		Presk.		-			
	110 P 1922.   145 P 1922.   175 GW Sent   125 GW Sent   126 GW Sent   127 GW Sent   128 GW Sent   129 P 1922.   120 GW Sent   125 GW Sent   126 GW Sent   127 GW Sent   128 GW Sent   129 P 1922.   120 GW Sent   121 GW Sent   121 GW Sent   125 GW Sent   126 GW Sent   127 GW Sent   128 GW Sent	$\begin{array}{ c c c c c c c c c c c c c c c c c c c$	Image: Image is a start of the sta	10 P 175 105 32 -0-5-54 Reg.   10 P 175 105 32 -0-5-54 Reg.   10 OF 155 104 10 -0-54 Reg.   11 OF 155 104 10 -0-54 Reg.   12 OF 155 104 10 -0-54 Reg.   13 OF 155 104 10 -0-54 Reg.   14 OF 155 104 10 -0-54 Reg.   15 OF 155 104 10 -0-54 Reg.		Image: Process of the state of the	0 P Compared to the second to

#### **Serial Redirector Function Maintains Original Master/Slave Connections**

The serial redirector function allows the commands of a serial master (command initiator) to be redirected to the serial slave (command executor) on another port. In addition, a serial master can operate simultaneously with EtherNet/IP masters without changing the DF1 architecture or software. With the serial redirector function, MGate™ EIP3000 gateways can establish redundant control of legacy slave devices that were originally designed to be controlled by a single serial master.

#### **ProCOM Implements Control via COM Port Mapping**

Each MGate<sup>™</sup> EIP3000 gateway supports virtual serial ports for the remote PC. You can connect to the MGate<sup>™</sup> EIP3000 through the COM port by using Moxa's Real COM driver, with the actual physical connection over the Ethernet. The gateway supports up to four virtual COM port connections and offers greater flexibility when designing redundant control systems.



### **Pull High/Low Resistors and Terminator Selection**

When using termination resistors to prevent serial signal reflection, it is important to set the pull high/low resistors correctly so that the electrical signal is not corrupted. Since no set of resistor values is universally compatible with all environments, the EIP3000 has DIP switches on the bottom panel for setting the termination and pull high/low resistor values.

#### **Built-In Isolation**

Complex device networks that incorporate high amperage devices could be subject to electrical signal distortion from electrical discharges, magnetic noise, or common mode transients. MGate<sup>™</sup> Series products solve this problem by using built-in optical isolation.

## **Specifications**

Ethernet Interface	
10/100BaseT(X) Ports (RJ45 connector)	2 Auto MDI/MDI-X connection
Ethernet Software Features	
Industrial Protocols	Ethernet/IP (PCCC)
Configuration Options	MGate Manager Telnet Console
Management	ARP DHCP Client SNMPv1 TCP/IP Telnet UDP
MIB	RFC1213, RFC1317
Serial Interface	
No. of Ports	MGate EIP3170 models: 1 MGate EIP3270 models: 2
Connector	MGate EIP3170 models: DB9 male for RS-232, Terminal block for RS-422/485 MGate EIP3270 models: 2 x DB9 male
Serial Standards	RS-232 RS-422
Baudrate	1200 bps to 921.6 kbps
Data Bits	8
Parity	None Even Odd
Stop Bits	1, 2
Flow Control	RTS/CTS DTR/DSR (RS-232 only)
Isolation	I models: 2 kV
Serial Signals	
RS-232	TxD, RxD, RTS, CTS, DTR, DSR, DCD, GND
RS-422	Tx+, Tx-, Rx+, Rx-, GND
Serial Software Features	
Industrial Protocols	DF1



## DF1 (Transparent)

DF1 (Transparent)			
Mode	Full duplex		
Max. No. of Client Connections	8		
Power Parameters			
Input Voltage	12 to 48 VDC		
Input Current	MGate EIP3170/EIP3170-T/EIP3270/EIP3270-T: 435 mA @ 12 VDC MGate EIP3170I/EIP3170I-T: 555 mA @ 12 VDC MGate EIP3270I/EIP3270I-T: 510 mA @ 12 VDC		
Relays			
Contact Current Rating	Resistive load: 1 A @ 30 VDC		
Physical Characteristics			
Housing	Plastic top cover, metal bottom plate		
IP Rating	IP30		
Dimensions (with ears)	29 x 89.2 x 124.5 mm (1.14 x 3.51 x 4.90 in)		
Dimensions (without ears)	29 x 89.2 x 118.5 mm (1.14 x 3.51 x 4.67 in)		
Weight	MGate EIP3170 models: 360 g (0.79 lb) MGate EIP3270 models: 380 g (0.84 lb)		
Environmental Limits			
Operating Temperature	Standard Models: 0 to 60°C (32 to 140°F) Wide Temp. Models: -40 to 75°C (-40 to 167°F)		
Storage Temperature (package included)	-40 to 85°C (-40 to 185°F)		
Ambient Relative Humidity	5 to 95% (non-condensing)		
Standards and Certifications			
EMC	EN 55032/35		
EMI	CISPR 32, FCC Part 15B Class A		
EMS	IEC 61000-4-2 ESD: Contact: 6 kV; Air: 8 kV IEC 61000-4-3 RS: 80 MHz to 1 GHz: 10 V/m IEC 61000-4-4 EFT: Power: 4 kV; Signal: 2 kV IEC 61000-4-5 Surge: Power: 4 kV IEC 61000-4-6 CS: 10 V IEC 61000-4-8 PFMF IEC 61000-4-11		
Safety	IEC 60950-1 UL 60950-1 EN 62368-1 UL 508		
Hazardous Locations	ATEX Class I Division 2 IECEx <sup>1</sup>		
Freefall	IEC 60068-2-32		
Shock	IEC 60068-2-27		

1. If you need an IECEx certificate for this product, please contact a Moxa sales representative.



Vibration	IEC 60068-2-6 IEC 60068-2-64
Maritime	MGate EIP3170 models: DNV
MTBF	
Time	MGate EIP3170: 1,344,456 hrs MGate EIP3170-T: 1,344,456 hrs MGate EIP3170I: 1,344,456 hrs MGate EIP3170I-T: 1,344,456 hrs MGate EIP3270: 1,204,573 hrs MGate EIP3270-T: 1,204,573 hrs MGate EIP3270I: 1,204,573 hrs
Standards	Telcordia SR332
Warranty	
Warranty Period	5 years
Details	See www.moxa.com/warranty
Package Contents	
Device	1 x MGate EIP3170/EIP3270 Series gateway
Documentation	1 x quick installation guide 1 x warranty card

## **Dimensions**

Unit: mm (inch)



# **Ordering Information**

Model Name	No. of Serial Ports	Serial Connector	Serial Isolation	Operating Temp.
MGate EIP3170	1	RS-232: DB9 male RS-422/485: Terminal block	-	0 to 60°C
MGate EIP3170I	1	RS-232: DB9 male RS-422/485: Terminal block	2 kV	0 to 60°C
MGate EIP3270	2	DB9 male	-	0 to 60°C
MGate EIP3270I	2	DB9 male	2 kV	0 to 60°C
MGate EIP3170-T	1	RS-232: DB9 male RS-422/485: Terminal block	-	-40 to 75°C
MGate EIP3170I-T	1	RS-232: DB9 male RS-422/485: Terminal block	2 kV	-40 to 75°C
MGate EIP3270-T	2	DB9 male	-	-40 to 75°C

# Accessories (sold separately)

Cables	
CBL-F9M9-150	DB9 female to DB9 male serial cable, 1.5 m
CBL-F9M9-20	DB9 female to DB9 male serial cable, 20 cm
Connectors	
Mini DB9F-to-TB	DB9 female to terminal block connector
Power Cords	
CBL-PJTB-10	Non-locking barrel plug to bare-wire cable

© Moxa Inc. All rights reserved. Updated Apr 22, 2024.

This document and any portion thereof may not be reproduced or used in any manner whatsoever without the express written permission of Moxa Inc. Product specifications subject to change without notice. Visit our website for the most up-to-date product information.

